

21cm prime focus receiver (1260-1510 MHz)

This system can be used for sensitive continuum, spectroscopy, and pulsar observations. Additionally, it will be employed in search-programs for space-debris. Be aware, that this band may be influenced by RFI. The central horn has two circular polarizations, each of the outer six horns two linear polarizations.

Calibration Information

Frequency [GHz]	Channel	Polarisation	Tcal [K]	Tsys [K]	Sensitivity [K/Jy]	SEFD [Jy]	Aperture Eff. [%]	TMB/S [K/Jy]	Main Beam Eff. [%]	FWHM [arcsec]	Last update
1.400	A	LCP	4.5	25	1.5	17	54	2.0	75	~550	Dec 2007
normalized Gain curve ($G = A0 + A1 \cdot Elv + A2 \cdot Elv^2$)							Observed in confirmed				
A0 = 1.0		A1 = 0.0		A2 = 0.0		Dec 2007					

Comments:

- Values for the other horns will follow

Version description for OBSINP

RX Name	Wavelength [cm]	Frequency (center) [GHz]	Nr. of Horns
P217mm 7-Beam (1.26-1.51 GHz)	21.0	1.26-1.51 (1.4)	7
Version:	Comment		
1. Beam-Park-Mode (BW: 47 MHz)	Version for space debris search		
2. Continuum/Line (XFFTS) (BW: 100 MHz)	Continuum/Line with the central horn (+1) only.		
3. Pulsar (BW: 300 MHz)	Pulsar wide band filter		
4. Line with AFFTS only	HI Survey		
Horn offsets [arcsec]	(0.0,0.0),(-785.0,453.0),(0.0,906.0),(785.0,453.0),(785.0,-453.0),(0.0,-906.0),(-785.0,-453.0)		

Channel assignment in the MBFITS data files

Note that the narrow line and VLBA IF channels are usually only available when the specific line version of the receiver was selected. In addition for most receivers with narrow line channels the cables at the patch board need to be connected by the receiver group.

To select different channel numbers in OBSINP, the online plot, or the toolbox the numbers have to be specified like $c(1)+c(2)$ to add channel 1 and 2. E.g. channel 1 and 2 contain the LCP and RCP broadband channels, then "OnlPlot pen='c(1)+c(2)'" or "toolbox use='c(1)+c(2)'" will select these channels. In OBSINP the pen can be directly specified in the receiver selection menu.

Abbreviations:

SB: narrow band channel (Schmalband-Kanal), 100 MHz band width

BB: digital broad band channel (Breitband-Kanal), band width varies for different receivers

VLBA: VLBA IF, 500 MHz band width

BW: band width

TP: total power

21cm-7beam PFK (only 2 out of 7 horns for continuum)			
Channel	IF	Pol.	Comment
1	SB	LCP	central horn 1, TP A
2	SB	RCP	central horn 1, TP B
3	SB	cross	central horn 1, cos AB
4	SB	cross	central horn 1, sin AB
5	SB	linear	horn 2, TP A
6	SB	linear	horn 2, TP B
7	SB	cross	horn 2, cos AB
8	SB	cross	horn 2, sin AB

Tcal and Tsys measurements

TODO

From:
<https://eff100mwiki.mpifr-bonn.mpg.de/> - Effelsberg 100m Teleskop

Permanent link:
https://eff100mwiki.mpifr-bonn.mpg.de/doku.php?id=information_for_astronomers:rx:p217mm&rev=1363093443

Last update: 2013/09/30 11:55

