

# 6.5mm primary focus receiver (41050-49700 MHz)

This receiver was build for spectroscopic observations. Its frequency range is divided into two channels (41-45 GHz, 45-50 GHz), each with its own (linearly polarized) feed horn separate by 107 arcsec.

## Calibration Information

Frequency [GHz]	Channel	Polarisation	Tcal [K]	Tsys [K]	Sensitivity [K/Jy]	SEFD [Jy]	Aperture Eff. [%]	TMB/S [K/Jy]	Main Beam Eff. [%]	FWHM [arcsec]	Last update
41.5	A	linear	11.0	170	0.61	280	36	1.3	47	23.4	Feb 2008
44.0	A	linear	9.0	153	0.43	358	25	1.3	33	22.0	Feb 2008
48.0	B	linear	7.0	135	0.28	498	17	1.3	22	20.5	Feb 2008
49.0	B	linear	5.0	127	0.25	508	13	1.4	17	19.0	Feb 2008

**normalized Gain curve ( $G = A0 + A1 \cdot Elv + A2 \cdot Elv^2$ )** **Observed in confirmed**

A0=0.68500	A1=1.7763E-2	A2=-2.4878E-4	Feb 2008	
------------	--------------	---------------	----------	--

## Comments:

- Gain curves are opacity corrected. Opacity was  $\tau=0.12$  during the observations. Values between 0.12 and 0.15 should be typical for good weather conditions at this frequency.

## Version description for OBSINP

RX Name	Wavelength [cm]	Frequency (center) [GHz]	Nr. of Horns
<b>P6mm (41,1-49.8 GHz,6.5mm)</b>	0.65	41.05-49.8	2
<b>Version:</b>	<b>Comment</b>		
1. Cont./Line: 41,05-45,5 GHz (BW: 500 MHz)	Continuum and spectroscopy 1st freq. range, horn 1		
2. Cont./Line: 45,25-49,7 GHz (BW: 500 MHz)	Continuum and spectroscopy 2nd freq. range, horn 2		
<b>Horn offsets [arcsec]</b>	(0.0,0.0), (0.0,107.0)		

## Channel assignment in the MBFITS data files

Note that the narrow line and VLBA IF channels are usually only available when the specific line version of the receiver was selected. In addition for most receivers with narrow line channels the cables at the patch board need to be connected by the receiver group.

To select different channel numbers in OBSINP, the online plot, or the toolbox the numbers have to be

specified like  $c(1)+c(2)$  to add channel 1 and 2. E.g. channel 1 and 2 contain the LCP and RCP broadband channels, then "OnlPlot pen='c(1)+c(2)'" or "toolbox use='c(1)+c(2)'" will select these channels. In OBSINP the pen can be directly specified in the receiver selection menu.

Abbreviations:

SB: narrow band channel (Schmalband-Kanal), 100 MHz band width

BB: digital broad band channel (Breitband-Kanal), band width varies for different receivers

VLBA: VLBA IF, 500 MHz band width

BW: band width

TP: total power

6.5mm PFK			
Channel	IF	Pol.	Comment
1	BB	linear	Horn 1, TP A, 41.05-45.5 GHz
2	BB	linear	Horn 2, TP A, 45.25-49.7 GHz
3	VLBA	linear	Horn 1, TP A, 41.05-45.5 GHz
4	VLBA	linear	Horn 2, TP A, 45.25-49.7 GHz

## Tcal and Tsys measurements

From:  
<https://eff100mwiki.mpifr-bonn.mpg.de/> - Effelsberg 100m Teleskop

Permanent link:  
[https://eff100mwiki.mpifr-bonn.mpg.de/doku.php?id=information\\_for\\_astronomers:rx:p6mm&rev=1363093669](https://eff100mwiki.mpifr-bonn.mpg.de/doku.php?id=information_for_astronomers:rx:p6mm&rev=1363093669)

Last update: 2013/09/30 12:11

