

P170mm - ultra broad-band prime focus receiver (1300-6000 MHz)

This is an ultra broad band (UBB) 2-channel system covering a range from 1300 to 6000 MHz.

Overview

RX Name	Band	Frequency range [GHz]	Polarisation	Nr. of Horns	Horn position relativ to center of focus cabin
P170mm	L/S/C	1.3-6.0	dual-linear	1	Az: 0 arcsec, Elv: 0 arcsec

Calibration Information

Frequency [GHz]	Channel	Polarisation	Tcal [K]	Tsys [K]	Sensitivity [K/Jy]	SEFD [Jy]	Aperture Eff. [%]	TMB/S [K/Jy]	Main Beam Eff. [%]	FWHM [arcsec]	Last update
1.41	A+B	2x lin	5.7	19.8	1.3	15.2	46	1.90	68	569	first observations
1.665	A+B	2x lin	6.7	20.6	1.3	15.8	46	1.78	73	497	first observations
2.35	A+B	2x lin	8.8	16.1	1.3	12.4	46	1.68	77	363	first observations
3.35	A+B	2x lin	11.0	16.5	1.3	12.7	46	1.66	78	256	first observations
4.85	A+B	2x lin	12.5	18.8	1.3	14.5	46	1.71	76	174	first observations
5.54	A+B	2x lin	11.6	19.0	1.3	14.6	46	1.64	79	156	first observations
normalized Gain curve ($G = A0 + A1 \cdot Elv + A2 \cdot Elv^2$)								Observed in confirmed			
A0 = 1.0		A1 = 0.0		A2 = 0.0							

Comments:

- The system delivers two basebands, 1.3-2.6 GHz and 3.0-6.0 GHz. Currently, it is not possible to record both bands in parallel for continuum or spectroscopic observations, except for pulsar timing and search mode observations.

Available receiver versions (for OBSINP)

Version	Description	Details
EDDPOL	spectro-polarimeter backend for continuum observations in the lower band	with 64k channels
EDDPOL3G	spectro-polarimeter backend for continuum observations in the upper band	with 64k channels
EDD_PULSAR	pulsar backend	

Last
update: information_for_astronomers:rx:p170mm https://eff100mwiki.mpifr-bonn.mpg.de/doku.php?id=information_for_astronomers:rx:p170mm&rev=1733216005
2024/12/03 09:53

From:
<https://eff100mwiki.mpifr-bonn.mpg.de/> - **Effelsberg 100m Teleskop**

Permanent link:
https://eff100mwiki.mpifr-bonn.mpg.de/doku.php?id=information_for_astronomers:rx:p170mm&rev=1733216005

Last update: **2024/12/03 09:53**

